

CHIRP-Baofeng Menu Cross Reference

CHIRP Basic Settings Tab	
CHIRP Basic	Baofeng Menu
Carrier Squelch Level	0 SQL
Battery Saver	3 SAVE
Backlight Timeout	6 ABR
Display Mode (A)	21 MDF-A
Display Mode (B)	22 MDF-B
Beep	8 BEEP
Timeout Timer	9 TOT
Standby LED Color	29 WT-LED
RX LED Color	30 RX-LED
TX LED Color	31 TX-LED
Roger Beep (TX)	39 ROGER
Roger Beep (RX)	40 A/B-BP

CHIRP Advanced Settings Tab	
CHIRP Advanced	Baofeng Menu
VOX Sensitivity	4 VOX
Dual Watch	7 TDR
Dual Watch TX Priority	34 TDR-AB
Alarm Mode	32 AL-MOD
Voice	14 VOICE
Scan Resume	18 SC-REV
Busy Channel Lockout	23 BCL
Automatic Key Lock	24 AUTOLK
Squelch Tail Eliminate (HT to HT)	35 STE
Squelch Tail Eliminate (repeater)	36 RP-STE
STE Repeater Delay	37 RPT-RL

CHIRP Work Mode Settings Tab	
CHIRP Work Mode	Baofeng Menu
VFO A/B Shift	25 SFT-D
VFO A/B Offset	26 OFFSET
VFO A/B Power	2 TXP
VFO A/B Bandwidth	5 WN
VFO A/B PTT ID	17 S-CODE
VFO A/B Tuning Step	1 STEP

CHIRP DTMF Settings Tab	
CHIRP DTMF	Baofeng Menu
PTT ID Code	17 S-CODE
ANI ID	15 ANI-ID
DTMF Sidetone	16 DTMFST
PTT ID Delay	20 PTT-LT

CHIRP Memory Properties General Tab	
CHIRP Memory Properties General	Baofeng Menu
Tone	13 T-CTCS
ToneSql	11 R-CTCS
DTCS Code	12 T-DCS
RX DTCS Code	10 R-DCS
Duplex	25 SFT-D
Offset	26 OFFSET
Mode	5 WN
Power	2 TXP

CHIRP Memory Properties Other Tab	
CHIRP Memory Properties Other	Baofeng Menu
BCL	23 BCL
PTT ID	19 PTT-ID
PTT ID Code	17 S-CODE